



TECHNICAL / FIELD SERVICE REPORT

SUBJECT: Programming of AF-300-C11 Motor Drive for Guzzo Consoles (4)

WRITTEN BY:: Dan Reiter, Engineering

DATE: September 19, 2002

Following are the functions and programmed codes for the FUJI AF-300 C11 drive:

<u>FUNCTION:</u>	<u>CODE:</u>	<u>DESCRIPTION:</u>
F0	0	Enable Programming / Data Change
F1	4	Frequency Command
F2	1	Enable Remote Control
F7	3.0	Motor Acceleration Time (Recommended by BIG SKY)
F8	3.0	Motor De-Acceleration Time (Recommended by BIG SKY)
F14	2	Motor Re-Start after power interruption
F15	60	Maximum Frequency / Speed
F16	60	Minimum Frequency / Speed
F26	15	Motor Sound Control
F27	0	Motor Noise